

Typ		HFD 111			HFD 212			
Bestellnummer		414 140			414 150			
EAN-Code		402618320089			402618320102			
		1-fach Abzweiger			2-fach Abzweiger			
Frequenzbereich	[MHz]	5...2400						
Maximaler Innenleiter Ø	[mm]	1,13						
Verteildämpfung								
5 - 40 MHz	[dB]	10,5			10,5			
40 - 1000 MHz	[dB]	10,5			11			
1000 - 2050 MHz	[dB]	12			11,5			
2050 - 2400 MHz	[dB]	13,5			13			
Durchgangsdämpfung								
5 - 40 MHz	[dB]	2,5			3,5			
40 - 1000 MHz	[dB]	1,5			2,5			
1000 - 2050 MHz	[dB]	3,0			4,5			
2050 - 2400 MHz	[dB]	4,0			5,5			
Entkopplungsdämpfung								
		Stich / Stamm			Stich / Stamm		Stich / Stich	
5 - 40 MHz	[dB]	10,5			17		15	
40 - 1000 MHz	[dB]	10,5			25		30	
1000 - 2050 MHz	[dB]	12			20		25	
2050 - 2400 MHz	[dB]	13,5			15		20	
Reflexionsdämpfung								
		Eingang	Ausgang	Stich	Eingang	Ausgang	Ausgang	Stich
5 - 40 MHz	[dB]	11	13	5	8	13	10	5
40 - 1000 MHz	[dB]	14	12	14	14	12	14	13
1000 - 2050 MHz	[dB]	14	10	14	15	10	15	12
2050 - 2400 MHz	[dB]	8	10	10	8	10	10	10